Provided by:



www.atecorp.com (800) 404-ATEC



# 260 SERIES GROUND BOND TESTERS



#### 5 PROGRAMMABLE MEMORIES

#### EASILY AUTOMATE FOR DATA COLLECTION

#### ADVANCED SECURITY SETTINGS

MILLIOHM OFFSET FUNCTION FOR ACCURATE GROUND BOND TESTING

## REDUNDANT HARDWARE SAFETY INTERLOCK

#### PORTABLE, RUGGED DESIGN

EASILY SAFEGUARD YOUR WORKSTATION WITH PPE ACCESSORIES Our 260 Series makes Ground Bond testing simple. Choose between two simple, easy-to-use Ground Bond testers that provide the output current that satisfy NRTL specifications. With an intuitive interface that allows you to set-up a test in seconds and practical security settings, our 260 Series can easily be deployed in both laboratory and production line environments.



## **RELEVANT APPLICATIONS**

#### APPLIANCE

INDUSTRIAL EQUIPMENT

MEDICAL

LABORATORY EQUIPMENT

WATER PUMPS

#### **264 SUPPLIED ACCESSORIES**

- 40 Amp High Current Lead 6 ft. (1.8m) 99-10725-01
- 40 Amp High Current Return Lead 6 ft. (1.8m) 99-10724-01
- 125-013-001 Input Power Cable USA
- Fuse 10 Amp (264 Model) 99-10783-01

## **266 SUPPLIED ACCESSORIES**

- 60 Amp High Current Lead 6 ft. (1.8m) 99-10239-01
- 60 Amp High Current Return Lead 6 ft. (1.8m) 99-10238-01
- 99-10164-01 Input Power Cable USA
- Fuse 12 Amp (266 Model) 99-10791-01

#### All testers come with all the accessories you need to run a test right out of the box.

#### **OPTIONS**

Description	264	266
Rear Outputs	•	•
USB Port	•	•
Display Voltage Drop	•	•





## SERIES FEATURES



## **260 SERIES SPECIFICATIONS**

#### INPUT

Voltage	264	100 - 120 VAC / 200 - 240 VAC ± 10% Auto Range
	266	100 - 240 VAC $\pm$ 10% Full Range
Frequency	50/60 Hz $\pm$ 5%	
Fuse	264	10A / 250 VAC Slow-Blow
	266	12A / 250 VAC Slow-Blow

#### **GROUND BOND TEST MODE**

Output Rating	264	3.0 - 40.0 AAC	
	266	3.0 - 60.0 AAC	
	Resolution: 0.1 A		
	Accuracy: $\pm$ (2% of setting + 0.1A)		
	264	Voltage 8 VAC (fixed)	
	266	Voltage 12 VAC (fixed)	
Output Frequency	50/60 Hz user selectable Accuracy: ± 0.1%		
Resistance Limit Settings	264	0 - 150 mΩ for 30.1 - 40.0 A 0 - 200 mΩ for 10.1 - 30.0 A 0 - 600 mΩ for 3.0 - 10.0 A	
	266	0 - 150 mΩ for 30.1 - 60.0 A 0 - 200 mΩ for 15.1 - 30.0 A 0 - 600 mΩ for 3.0 - 15.0 A	
	Resolution: 1 m $\Omega$ Accuracy: ± (2% of setting + 2 m $\Omega$ )		
Offset Limit Settings	0 - 100 m $\Omega$ Resolution: 1 m $\Omega$ Accuracy: ± (2% of setting + 2 m $\Omega$ )		
Dwell Timer	0, 0.5 - 240.0 sec, (0=continuous), 0.1 sec/step		
Ramp Timer	0.1 sec fixed		
Measurement Current	264	0.0 - 40.0 AAC	
	266	0.0 - 60.0 AAC	
	Resolution: 0.1 A Accuracy: $\pm$ (3% of reading + 0.1 A)		
Ohmmeter	264	0 - 600 mΩ	
		Resolution: 1 m $\Omega$ Accuracy: ± (3% of reading + 3 m $\Omega$ ) for 3 - 5.9 A, ± (2% of reading + 2 counts) for 6 - 40A	
	266	0 - 600 mΩ	
		Resolution: 1 m $\Omega$ Accuracy: ± (3% of reading + 3 m $\Omega$ ) for 3 - 5.9 A ± (2% of reading + 2 m $\Omega$ ) for 6 - 60 A	

#### **GENERAL SPECIFICATIONS**

SEITERNE STEERIE				
Memories	5			
Remote I/O	Input:	Test, Reset, Interlock		
	Output:	Pass, Fail, Test-in-Process		
	Hardware Interlock - a relay on the high voltage output opens when the Interlock signal is disabled.			
Voltage Drop Display (optional)	Display the voltage drop across the circuit instead of the resistance measurement.			
Voltage Limit Settings	264	0.00 - 6.00 VAC		
	266	0.00 - 9.00 VAC		
	Resolution: 0.01 V Accuracy: ± (2% of setting + 0.02 V)			
Offset Limit Settings	264	0.00 - 4.00 VAC		
	266	0.00 - 6.00 VAC		
	Resolution: 0.01 V Accuracy: ± (2% of setting + 0.02 V)			
Security	Option to turn On or Off, when On you can switch between two security levels:			
	1. Run - Operator can only run a test. No ability to change memory locations or edit test parameters.			
	2. Mem - Operator can run a test and change memory locations. No ability to edit test parameters.			
Safety Mark	CE/cTUVus			
<b>Dimensions</b> (W x H x D)	264	8.5" x 3.5" x 11.81" (215 x 88 x 300 mm)		
	266	16.93" x 5.20" x 11.81" (430 x 132 x 300 mm		
Weight	264	9.25 lbs. (4.3 Kg)		
	266	20.25 lbs. (9 Kg)		

Specifications subject to change without notice.