



**Advanced Test Equipment Rentals**  
**www.atecorp.com 800-404-ATEC (2832)**

**T 3090**  
**T 3090 T**  
**T 3090 SX**  
**T 3090 SX-T**

**Megger**

## **Digital Time Domain Reflectometer**



*Upgrades &  
Up- / Downloads  
with Memory Stick  
...only one in the industry*

*....the TDR with Windows CE<sup>®</sup> embedded software  
for true Windows<sup>®</sup> software style operation*

# Technical Specifications T3090, T3090 T, T3090 SX, T3090 SX-T

Using a radar to pre-locate faults will save time and reduce cable damage. The **T 3090** is designed to be most user-friendly radar on the market! Advanced features include One Button Operation, Automatic Gain and a Large Color Screen. The T 3090 will automatically 'read' the cable end and display the fault distance with a single thump. Our interactive '**Step-By-Step Easy Mode**' will help train (or re-train) the occasional user **while he is on the job!** The optional '**Sectionalizing Mode**\*\* will quickly sectionalize faults in loops or radial systems.

## Measuring Range (ft, m , m sec or NVA)

Continuously from 0 ft to 25,000 ft

X Models 0 ft to 100,000 ft\*\*\*

## Fault Locating Methods

ARM® (HV Arc Reflection Mode)

Surge Pulse (optional, T 3090 SX models)

Sectionalizing (optional, T3090T models)

LV TDR (use for secondary fault locating)

## Pulse Width:

Automatic with range selection or manual  
50 ns, 100 ns, 200 ns, 500 ns, 1µs,  
2 µs, 5 µs, 10 µs

## Pulse Shape:

special pulse shape for high resolution

## Sampling Rate: 100 MHz

## Accuracy:

<= 2.5 feet depending on displayed range

## Screen:

High Brite 1200 nits 10.4" diagonal  
VGA Color TFT LC-Display,

## Velocity of propagation:

Via cable menu or manual between  
140 ft/µs ... 492 ft/µs (also in m/µs)

## Display Choices:

live trace always visible,  
stored reference & fault trace

Up to 10 superimposed traces visible on  
display for comparison

## Weight / Dimensions: 17lbs, 11" x 15" x 6"

## Operator Men Styles:

### Quick Steps® Style Menu

Automatic fault distance location  
Automatic "short" or "open" assessment

### Step-by-Step Easy Style Menu

Unique real time on screen tutorial for :

**fault locating – hipot – pinpointing – burning**  
**for all HDW & some competitor's thumpers**

### Expert Style Menu

**NOTE:** user can custom configure and pass -  
word protect the specific TDR features available  
in each of the 3 menu styles (22), depending on  
the experience & skill level of the operator

## Optional Fault locating Programs

### **Sectionalizing**

Automatic sectionalizing in loops, identifying  
cable fault between 2 closest transformers

### **Surge Pulse**

fault locating with TDR as transient recorder

## Convenient Features:

### **PC Communication:**

Upgrade & Up & Download via USB Port

### **Power Requirements:**

115 V / 230 V, 50 / 60 Hz

### **Operating Temperature:**

-5 F to 105 F (-20 °C + 40 °C)

\*ARM® is a Trademark of HDW Electronics, Inc.

Quick Steps® is applied for Trademark by HDW Electronics, Inc.

\*\* Sectionalizing, Patent No.US 6,683,459 B2

\*\*\* Available 06/2012

## UK

Archcliffe Road, Dover  
CT17 9EN England  
T +44 (0) 1 304 502101  
F +44 (0) 1 304 207342  
UKsales@megger.com

## GERMANY

MEGGER/SebaKMT  
D 96148 Baunach  
Dr.Herbert-Iann Str.6  
T +49-9544-680  
F +49-9544-2273  
Sales@sebakmt.com

## UNITED STATES

4271 Bronze Way  
Dallas, TX 75237-1019 USA  
T 1 800 723 2861 (USA only)  
T +1 214 333 3201  
F +1 214 331 7399  
USsales@megger.com

## OTHER TECHNICAL SALES OFFICES

Valley Forge USA, College Station  
USA, Täby SWEDEN, Sydney  
AUSTRALIA, Ontario CANADA,  
Trappes FRANCE, Oberursel  
GERMANY, Mumbai INDIA,  
Johannesburg SOUTH AFRICA, Aargau  
SWITZERLAND, Chonburi THAILAND,  
and Dubai UAE